OPTIONS



IC-M85E

SPECIFICATIONS

		IC-M85E			
GENERAL		Marine channels	PMR channels		
Frequency coverage Tx Rx		156.000–161.450 MHz 156.000–163.425 MHz	136.000–174.000 MHz		
Usable channel groups, Number of channels		INT, USA* channels (* Varies according to version)	100 PMR channels		
Type of emissions	EUR, UK FRG	16K0G3E	16K0F3E/8K50F3E 14K0F3E/8K50F3E		
Channel spacing	EUR, UK FRG	25 kHz	25/12.5 kHz 20/12.5 kHz		
Power supply r		7.2 V DC nominal			
Current drain (approximate) Tx (at 5 W) Rx Max. audio		1.5 A 0.45 A			
Antenna imped			Ω		
Operating tempe		–15 °C to +55 °C	–25 °C to +55 °C		
Dimensions (W×H×D) (Projections not included)		$56 \times 92 \times 29$ mm (With BP-290)			
Weight (approxi	mate)	246 g (with BP-290,	FA-SC58V and MBB-3)		
TRANSMITTE	R				
Output power (at 7.2 V DC)		5/3/1 W	5/3/1 W		
Max. frequency deviation	/ EUR, UK FRG	±5.0 kHz	±5.0 kHz (Wide) ±2.5 kHz (Narrow) ±4.0 kHz (Wide) ±2.5 kHz (Narrow)		
Frequency stat	oility	±1.5 kHz			
Spurious emis	sions	0.25 µW (≤2 GHz),1.0 µW (>2 GHz)			
Residual modu	Ilation	40 dB	40 dB (Wide) 34 dB (Narrow)		
Audio harmoni	c distortion	10% (at 60% deviation)			
Modulation lim	iting	60–100% of ma	ximum deviation		
RECEIVER					
Sensitivity (at 20 dB SINAD)		-4 dBµ emf typical	-4 dBµ emf typical (Wide -2 dBµ emf typical (Narrow		
Adjacent channel selectivity		70 dB	70 dB (Wide) 60 dB (Narrow)		
Spurious response		70 dB			
Intermodulation		68 dB	65 dB		
Hum and noise		40 dB	40 dB (Wide), 34 dB (Narrow		
Audio output Internal SP		700 mW typical (at 10% distortion with 12 Ω load at 1 kH			
	External SP	700 mW typical (at 10% distortion with 8 Ω load at 1 kHz)			

Applicable U.S. Military Specifications & IP Rating

Standard	MIL 810 G		
Standard	Method	Procedure	
Low Pressure	500.5	I, II	
High Temperature	501.5	I, II	
Low Temperature	502.5	I, II	
Temperature Shock	503.5	I–C	
Solar Radiation	505.5	I	
Rain Blowing/Drip	506.5	I, III	
Humidity	507.5	II	
Salt Fog	509.5	-	
Dust Blowing	510.5	I	
mmersion	512.5	I	
Vibration	514.6	I	
Shock	516.6	I, IV	

IP67 (Dust-tight and waterproof protection)

SOFTWARE

E-mail: sales@icombrazil.co

+55 (31) 3582 8987

Fax:

• RS-BC225 : Intelligent charger software for Windows® PC. For use with BC-225.

E-mail: info@icomuk.co.uk

http://www.icomuk.co.uk

lcom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in Japan, the United States, the United Kingdom, Germany, France, Spain, Russia, Australia, New Zealand and/or other countries. AQUAQUAKE is a trademark of Icom Incorporated. Windows is either a registered trademark or a trademark of Microsoft Corporation in the United States and/or other countries. All other trademarks are the properties of their respective holders.

Icom Inc. 1-1-32, K	amiminami, Hirano-Ku, Osaka 547-0003, 🕻	Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013	www.icom.co.jp/world	Count on us!
Icom America Inc. 12421 Willows Road NE, Kirkland, WA 98034, U.S.A. Phone: +1 (425) 454-8155 Fax: +1 (425) 454-1509 E-mail: sales@icomamerica.com URL: http://www.icomamerica.com	Icom (Europe) GmbH Communication Equipment Auf der Krautweide 24 65812 Bad Soden am Taunus, Germany Phone: +49 (6196) 76685-0 Fax: +49 (6196) 76685-50 E-mail: info@icomeurope.com URL: http://www.icomeurope.com	Icom France s.a.s. Zac de la Plaine, 1 Rue Brindejonc des Moulinais, BP 45804, 31505 Toulouse Cedex 5, France Phone: +33 (5) 61 36 03 03 Fax: +33 (5) 61 36 03 00 E-mail: icom@icom-france.com URL: http://www.icom-france.com	Your local distributor/dealer:	stributor/dealer:
Icom Canada	Icom Spain S.L.	Icom (Australia) Pty. Ltd.		
Glenwood Centre #150-6165 Highway 17A, Delta, B.C., V4K 5B8, Canada Phone: +1 (604) 952-4266 Fax: +1 (604) 952-0090 E-mail: info@icomcanada.com URL: http://www.icomcanada.com	Ctra. Rubi, No. 88 "Edificio Can Castanyer" Bajos A 08174, Sant Cugat del Valles, Barcelona, Spain Phone: +34 (93) 590 26 70 Fax: +34 (93) 589 04 46 E-mail: com@icomspain.com URL: http://www.icomspain.com	Unit 1 / 103 Garden Road, Clayton, VIC 3168 Australia Phone: +61 (03) 9549 7500 Fax: +61 (03) 9549 7505 E-mail: sales@icom.net.au URL: http://www.icom.net.au		
Icom Brazil	lcom (UK) Ltd.			
Rua Itororó, 444 Padre Eustáquio Belo Horizonte MG, CEP: 30720-450, Brazil Phone: +55 (31) 3582 8847	Blacksole House, Altira Park, Herne Bay, Kent, CT6 6GZ, U.K. Phone: +44 (0) 1227 741741 Fax: +44 (0) 1227 741742 E moil: inte @isemuk co.uk			

ĨCOM

Marine and PMR Hybrid for Professional Use ~OM A CH

IC-M85E

VHF MARINE TRANSCEIVER



Ultra Compact and Powerful Marine Handheld with PMR Features







[Actual Size]



VHF MARINE TRANSCEIVER IC-M85E

Compact and Lightweight

The IC-M85E is the most compact (W×H×D: 56 × 92 × 29 mm) and lightweight (weight: 246 g (with BP-290, FA-SC58V and MBB-3)) commercial grade marine and land mobile hybrid radio in the world*. * As of November 2017, researched by Icom.

Covering 136–174 MHz ((•)) **PMR Frequency**

In addition to VHF marine channels, the IC-M85E covers 136-174 MHz PMR channels. Up to 100 programmable channels are available for PMR use. Each channel is programmable with CTCSS and DTCS tone.

/ n \

Automated Emergency Alarm

The IC-M85E has three emergency related functions: the MOB Alarm, Man Down and Lone Worker functions. If one of these functions are activated, the radio automatically makes an emergency alarm.

Instant Operation with Multi-Function Button

Channel group changing (Marine \Leftrightarrow PMR) or the scrambler function ON/OFF can be assigned in

the multi-function button on the top panel*. The Key lock function can be activated by holding the button. * Ask your dealer for details.

The IC-M85E is built durable

to endure 1 m submersion for 30 minutes and dust-tight

protection. The radio also passes

MIL-STD-810 specifications.



button

700 mW Powerful Audio

Despite its compact body, the IC-M85E delivers 700 mW of loud audio. Clear communications is vital in noisy environments.

Private Conversation

The radio has a built-in Voice Scrambler and provides private communication between stations (32-code, compatible with UT-112 voice scrambler unit).

Supplied accessories;



* SE for Europe plug. SUK for UK plug. SV for Australia plug.



BP-290 battery pack BC-227 rapid charger BC-123S* AC adapter FA-SC58V antenna





And More

□AquaQuake[™] prevents audio degradation from a water-logged speaker

Internal VOX capability for hands-free operation

IP67 and MIL-STD

□14 hours of long battery life (TX: RX: Standby=5:5:90.) □5 W output power

The self check function checks internal temperature, and connected battery voltage (over voltage detection)

□Monitor function □Priority scan function

Dual/Tri-watch function for monitoring CH16 and/or call channel DFavorite channel function for quick access to often used channels



MBB-3 belt clip

Hand stran

Variety of Audio Accessories


Waterproof Speaker-Microphones

HM-236



HM-222 With 3.5 mm earphone i

Hands-Free Operation with Headsets



Earphones and Speaker Microphones for Noisy Environments



Stylish Operation with Tie-Clip Microphone and Earphones

